PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification 6 :
H03G 3/30

A1

(11) International Publication Number: WO 99/17444

(43) International Publication Date: 8 April 1999 (08.04.99)

(21) International Application Number: PCT/US98/20574

(22) International Filing Date: 30 September 1998 (30.09.98)

(30) Priority Data:
08/941,488 30 September 1997 (30.09.97) US

(71) Applicant: ROCKWELL SEMICONDUCTOR SYSTEMS, INC. [US/US]; 4311 Jamboree Road, Newport Beach, CA 92660-3095 (US).

(72) Inventor: VAKILIAN, Nooshin; 7 Trapani, Irvine, CA 92614 (US).

(74) Agent: ANDRAS, Joseph, C.; Suite 650, 650 Town Center Drive, Costa Mesa, CA 92626 (US).

(81) Designated States: JP, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).

Published
With international search report.

(54) Title: MULTI-LAYER CARRIER MODULE FOR POWER AMPLIFIER



(57) Abstract

A single multi-layer carrier module (30) is disclosed which carries the power amplifier (32) components in a GSM mobile digital cellular telephone. In a first embodiment of the present invention the power amplifier (32) and the power amplifier controller (33) are placed upon a ceramic or laminate carrier module (31) along with necessary connection circuitry. The carrier module (30) is then connected to the RF board. In a second preferred embodiment of the present invention the power amplifier (32), the power amplifier controller (33) and a voltage controlled oscillator (34) are placed upon the carrier module (30).

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

MULTI-LAYER CARRIER MODULE FOR POWER AMPLIFIER

FIELD OF THE INVENTION

The present invention relates generally to digital wireless communication systems, and more particularly, to a power amplifier system which incorporates multiple power amplifier components upon a single carrier module attached to the RF circuit board.

BACKGROUND OF THE INVENTION

Cellular telephone systems include a central base station and multiple hand held mobile cellular phones. The first generation of mobile cellular phones were analog based systems. They were bulky, large, and heavy. Further, the analog cellular phones had limited channel capacity, in that there was one allowed transmission per channel, causing excessive interference between users and other limitations of use.

The next generation of cellular phones used digital technology. Digital technology has allowed certain digital signal processing systems and modulation or transmission techniques within the cellular environment which enable a larger channel capacity for communications along with reduced interference and lower error rates within the transmissions.

The speed with which the public accepts the transition between generations of cellular phones, including the transition from the first generation analog mobile phones to the next generation digital phones, is dependent upon certain factors including the

cost of the phones, the ease with which they may be used, the transmission quality, and other features which are desired by consumers.

While the first generation analog mobile cellular phones were relatively the size of small books and difficult to carry, the next generation of digital cellular phones are comfortably pocket sized. Further, there is a continuing desire to reduce the size and cost of mobile cellular phone systems while still enabling more functionality and electronics systems within the hand-held cellular phone unit.

The standards currently used for digital cellular telephony are different throughout world. The most important current digital cellular telephone standards are IS-54B which is used in the United States, Global System for Mobile Communication (GSM) in Europe, and RCR-27 in Japan. Each of these standards include digital voice and data transmission capabilities.

Various bodies worldwide are currently developing new standards for the specification of even the next generation of mobile cellular telecommunications systems along with their increased functionality. Services offered by current wireless mobile systems are simply telephony and voice services supported by narrowband digital networks. However, there will be a demand for higher bandwidth services as more comprehensive data and information transmission services are provided within the digital cellular network. Thus, today's wireless interface must carry narrowband services effectively while providing the flexibility to carry higher bandwidth services as the demand increases.

Within the power amplifier control loop, an RF coupler may be used at the power amplifier output in order to couple the RF output from the power amplifier to the RF logarithmic detector input. A common directional coupler known in the art is available from Murata Manufacturing Co., Ltd., Japan as part number LDC20B200H0902.

As shown within figure 2, the input to the logarithmic detector upon the RF122 power amplifier controller should be within the range of -40 dBm to 10 dBm. The coupled signal is fed to the input of the RF power detector on the RF122. The output from the detector is a D.C. voltage that is proportional to the RF power at the RF power amplifier output.

The integrating error amplifier amplifies and integrates the voltage difference between the detector output and the power control input. The output of the integrator is fed to the gain shaping circuit which drives the gain control input of the external RF power amplifier. The integrator in the integrating error amplifier is used to stabilize the loop. The D.C. bias circuitry provides voltage bias to the RF122.

A common Voltage Controlled Oscillator may also be provided on the RF board as an input drive to the power amplifier. The Voltage Controlled Oscillator fits within a phase locked loop at the power amplifier input, which translates the complex spectrum up to the desired channel within the transmit band. A common Voltage Controlled Oscillator used in this application is available from Murata Manufacturing Co., Ltd., Japan as part number MQE550-902.

Each of the major components in the radio subsystem, the power amplifier, the power amplifier controller, and the voltage controlled oscillator are separate components installed on the RF board which requires space, connection circuitry and cost.

OBJECTS OF THE INVENTION

It therefore is an object of the present invention to provide an improved digital cellular mobile phone which is less expensive, smaller and easier to manufacture.

It is a further object of the present invention to provide an improved digital cellular mobile phone which has an RF circuit board which is more compact and easier to assemble.

It is yet a further object of the present invention to provide an improved digital cellular mobile phone which has less separate components upon the RF circuit board.

SUMMARY OF THE INVENTION

These and other objects and advantages are achieved by the present invention by providing a single multi-layer carrier module carrying the power amplifier and the power amplifier controller.

In a first embodiment of the present invention the power amplifier and the power amplifier controller are placed upon a ceramic carrier module along with necessary connection circuitry. The carrier module is

Representative functional elements which are currently anticipated to be included within the next generation of wireless communication networks include telephony, videotelephony, and high-speed data transmission. These services have varying and distinguishable needs, transmission characteristics and other requirements which affect the size, weight and cost of cellular technology, and specifically the mobile cellular phone unit.

Figure 1 shows a graphical block diagram depiction of the several major subsystems within a mobile digital cellular telephone 10 used today. These subsystems include a battery pack 11, a set of user interfaces 12 (including a microphone, a speaker, a keyboard and a display), a set of digital control and/or analog device drivers 13 for the user interfaces 12, digital processing and control systems 14, a radio subsystem 15 , and an antenna 16. As shown within figure 1, each of the subsystems within the digital cellular phone 10 are interrelated and provide power and control to each other.

The battery pack 11 initially provides power to both the digital control and analog drivers 13 and the digital processing and control systems 14. The analog drivers and control system 13 controls the user interfaces 12, as well as the radio subsystem 15 including separate components such as a power amplifier, a power amplifier controller and a voltage controlled oscillator.

The power amplifier system within the radio subsystem 15 provides output power for transmission. The radio subsystem 15 further includes a variety of passive and active RF components for transmission and

reception, as well as the power amplifier for transmission through the antenna 16. These radio subsystem components are all provided on an RF board.

A common power amplifier used in this environment is an integrated circuit chip that is used within GSM digital cellular systems. This is the RI 21005 RF power amplifier available from Rockwell Semiconductor Systems, Newbury Park, California. The RI 21005 RF power amplifier is a compact 20 pin Thin Shrink Small Outline Package (TSSOP) surface mount GSM power amplifier operating within the 880 - 915 MHZ cellular band with pulsed output power up to 4 W. The output match is realized outside of the power amplifier.

A common power amplifier controller is an integrated circuit chip that is used within GSM digital cellular systems. This is the RF122 RF power amplifier controller available from Rockwell Semiconductor Systems, Newport Beach, California. The RF122 RF power amplifier controller is an integrated, monolithic device used to control the transmitted power of MOSFET and MESFET power amplifiers. A graphical block diagram of the RF122 is shown in figure 2.

As shown in figure 2, the RF122 power amplifier controller consist of two sections: an RF detector and a gain controller. The RF122, in combination with a power amplifier, forms a power amplifier control loop where the power amplifier output power is controlled by a single analog control voltage that is input to the RF122. The RF122 consists of a logarithmic RF detector, an integrating error amplifier, a gain shaper, and D.C. bias circuitry. The RF122 device is also packaged within a 20 pin Thin Shrink Small Outline Package (TSSOP).

then connected to the RF board.

In the first embodiment of the present invention, the power amplifier module sits upon an RF board within a GSM digital cellular telephone, the module includes (1) a power amplifier, which is a heterojunction bipolar transistor, (2) a power amplifier controller, which further includes an RF detector and a gain controller, (3)an RF coupler attached to the module, the coupler being electrically attached to an output of the power amplifier and feeding a signal to the input of the power amplifier controller, (4) few passive components to provide input and output matching for the power amplifier and the necessary supporting circuitry for the control loop, and 5) a module substrate. The power amplifier, the power amplifier controller, and the coupler are attached to the module substrate. The coupler is a directional coupler and separating a forward power from a reflected power to maintain a constant output power. The module substrate includes multiple layers, the multiple layers allowing a lattice of connection circuitry to be formed to allow the power amplifier and the power amplifier controller to communicate with each other.

In a second preferred embodiment of the present invention the power amplifier, the power amplifier controller and a voltage controlled oscillator are placed upon a ceramic or laminate carrier module along with necessary connection circuitry. The carrier module is then connected to the RF board. The second preferred embodiment is constructed similarly to the first preferred embodiment, with the exception that the voltage controlled oscillator is attached to the top surface of the module substrate. The voltage controlled oscillator is attached to the electrical input of the

power amplifier to provide input drive.

BRIEF DESCRIPTION OF THE DRAWINGS

The features, organization, advantages and objects of this invention will be fully understood from the following detailed description and the accompanying drawings. The drawings contained herein are not considered to be accurate depictions of the embodiments of the invention, but are provided for illustrative purposes only and are to be interpreted in conjunction with the attached specification.

Figure 1 shows a graphical block diagram depiction of the several major subsystems within a mobile digital cellular telephone.

Figure 2 shows a graphical block diagram of a common power amplifier controller known in the art.

Figure 3 shows a graphical block diagram depiction of a first preferred embodiment of the present invention.

Figure 4 shows a more detailed graphical block diagram depiction of the first preferred embodiment of the present invention shown in Figure 3.

Figure 5 shows a graphical illustration of the carrier module of the preferred embodiment of the present invention.

Figure 6 shows a graphical block diagram depiction of a second preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

The following description is provided to enable any person skilled in the art to make and use the invention, and sets forth the best modes presently contemplated by the inventor for carrying out this invention. Various modifications, however, will remain readily apparent to those skilled in these arts, since the generic principals of the present invention have been defined herein.

The first preferred embodiment of the present invention is a multiple layer module power amplifier circuit chip made for GSM digital cellular telephones. The multiple layer module of the first preferred embodiment contains a heterojunction bipolar transistor power amplifier and a power amplifier controller which meet the GSM specification.

A block diagram depiction of the first preferred embodiment of the present invention is illustrated in figure 3, and includes a power amplifier 21, a power amplifier controller 22 and a coupler 23. As shown figure 3, the power amplifier receives the digital RF input 24, and outputs a signal through the coupler 23. The power amplifier controller 22 accepts its input 25 from the coupler 23 in order to create a feed back loop input 26 to the power amplifier 21.

A more detailed block diagram of the first preferred embodiment of the present invention is shown in figure 4. As shown in figure 4, the power amplifier controller of the preferred embodiment consists of two sections: an RF detector and a gain controller (integrator). The power amplifier controller and the

power amplifier form a power amplifier control loop where the power amplifier output power is controlled by a single analog control voltage.

In the event of a poor voltage standing wave ratio, the preferred embodiment to the present invention includes a built-in directional coupler which separates the forward power from the reflected power in order to maintain a constant output power. In the preferred embodiment of the present invention the power amplifier is designed with a bipolar gallium arsenide process that allows single supply operation while maintaining high efficiency and excellent dynamic range.

A graphical illustration of the carrier module of the preferred embodiment of the present invention is depicted in figure 5. As the shown in figure 5 , the carrier module 30, has multiple layers 31, which allows circuitry to be inlaid to enable the various power amplifier components to electrically communicate and interact with one another.

As shown in figure 5, in the preferred embodiments of the present invention, the power amplifier 32, the power amplifier controller 33 and a voltage control oscillator 34 all sit upon the top layer of the multiple layer carrier module 30. A coupler is inlaid below the surface of the carrier module on other lower layers 31. Other connection circuitry is also embedded within the multiple layers of the carrier module 30. Common insulation or packaging is provided in order to protect the power amplifier components attached to the top surface of the carrier module substrate.

The carrier module of the preferred embodiment of the present invention is ceramic or laminate. In the

preferred embodiment of the present invention the substrate is a B.T. laminate available from Details, Inc., Anaheim, California.

A second preferred embodiment of the present invention is depicted in the block diagram illustration shown in figure 6. As shown in figure 6, the carrier module 40 includes the same components as the carrier module depicted in figure 3 along with a voltage controlled oscillator 41. The second preferred embodiment illustrated in figure 6 operates in the same manner as the power amplifier system illustrated in figure 3 with the addition that the voltage controlled oscillator 41 is integrated on the carrier module to drive the power amplifier.

Those skilled in the art will appreciate that various adaptations and modifications of the just described preferred embodiment can be used and configured without departing from the scope and spirit of the invention. Therefore, it is to be understood that, within the scope of the appended claims, the invention may be practiced other than as specifically described herein.

CLAIMS

What is Claimed Is:

A power amplifier module upon an RF board within a digital cellular telephone, the module comprising:

a power amplifier;

a power amplifier controller; and

a module substrate, the power amplifier and the power amplifier controller attached to the module substrate, the substrate being attachable to the RF board.

2. The module of Claim 1 wherein the power amplifier is a heterojunction bipolar transistor.

3. The module of Claim 1 wherein the module meets a GSM specification.

4. The module of Claim 1, further comprising an RF coupler attached to the module, the coupler being electrically attached to an output of the power amplifier.

5. The module of Claim 4, wherein the coupler feeds a signal to the input of the power amplifier controller.

6. The module of Claim 5, wherein the coupler is a directional coupler which separates a forward power from a reflected power to maintain a constant output power.

7. The module of claim 1, wherein the power amplifier controller further includes an RF detector and a gain controller.

8. The module of Claim 1, wherein the power amplifier receives a single analog control voltage

signal and the power amplifier and the power amplifier controller form a power amplifier control loop.

9. The module of Claim 1, wherein the power amplifier is designed with a bipolar gallium arsenide process.

10. The module of Claim 1, wherein the module substrate further comprises multiple layers, the multiple layers providing a lattice of connection circuitry to allow the power amplifier an the power amplifier controller to communicate with each other.

11. The module of Claim 10, wherein the power amplifier, the power amplifier controller and a voltage controlled oscillator sit upon a top surface of the multiple layer module substrate.

12. The module of Claim 10, wherein a coupler is inlaid upon the multiple layer module substrate, the coupler being inlaid upon layers of the substrate below a top layer.

13. The module of Claim 10, wherein the substrate is BT laminate.

14. The module of Claim 1, further comprising a voltage controlled oscillator attached to the module substrate, the voltage controlled oscillator being connected at an input to the power amplifier.

15. A power amplifier module upon an RF board within a digital cellular telephone, the module comprising:

a power amplifier, the power amplifier being a heterojunction bipolar transistor;

a power amplifier controller, the power amplifier controller further including an RF detector and a gain controller;

an RF coupler attached to the module, the coupler being electrically attached to an output of the power amplifier, the

coupler feeding a signal to the input of the power amplifier controller, the coupler being a directional coupler and separating a forward power from a reflected power to maintain a constant output power;

a module substrate, the power amplifier, the power amplifier controller, and the coupler attached to the module substrate, the module substrate further comprises multiple layers, the multiple layers providing a lattice of connection circuitry to allow the power amplifier and the power amplifier controller to communicate with each other, the module substrate being attachable to the RF board.

16. The module of Claim 15, wherein the module meets a GSM specification.

17. The module of Claim 15, wherein the power amplifier receives a single analog control voltage signal and the power amplifier and the power amplifier controller form a power amplifier control loop.

18. The module of Claim 15, wherein the power

amplifier, the power amplifier controller and a voltage controlled oscillator sit upon a top surface of the multiple layer module substrate.

19. The module of Claim 15, wherein the coupler is inlaid upon the multiple layer module substrate, the coupler being inlaid upon layers of the substrate below a top layer.

20. The module of Claim 15, further comprising a voltage controlled oscillator, the voltage controlled oscillator being electrically connected at an input to the power amplifier, the voltage controlled oscillator being attached to the top surface of the module substrate.



FIG. 1



FIG. 2

3/6

FIG. 3



FIG. 4





FIG. 5



FIG. 1



FIG. 2

FIG. 6



INTERNATIONAL SEARCH REPORT

International application No.
PCT/US98/20574

A. CLASSIFICATION OF SUBJECT MATTER
IPC(6) :H03G 3/30
US CL :330/279
According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 330/279, 65, 66, 286, 307; 375/345; 455/126, 128

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

NONE

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

NONE

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5,142,239 A (BRAYTON ET AL.) 25 August 1992 (25/08/92), see Fig. 2 and col. 4, lines 64-66.	1-20
X	US 5,450,046 A (KOSUGI ET AL.) 12 September 1995 (12/09/95), see Fig. 6 and col. 6, lines 50-62.	1-20

☐ Further documents are listed in the continuation of Box C. ☐ See patent family annex.

*	Special categories of cited documents:	"T"	later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"A"	document defining the general state of the art which is not considered to be of particular relevance	"X"	document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"E"	earlier document published on or after the international filing date	"Y"	document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
"L"	document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	"&"	document member of the same patent family
"O"	document referring to an oral disclosure, use, exhibition or other means		
"P"	document published prior to the international filing date but later than the priority date claimed		

Date of the actual completion of the international search	Date of mailing of the international search report
24 NOVEMBER 1998	12 JAN 1999
Name and mailing address of the ISA/US Commissioner of Patents and Trademarks Box PCT Washington, D.C. 20231 Facsimile No. (703) 305-3230	Authorized officer JAMES B. MULLINS Telephone No. (703) 308-4912

Form PCT/ISA/210 (second sheet)(July 1992)*

3/6

FIG. 3



FIG. 4





FIG. 5

FIG. 6